

Code: AE72

Subject: MICROWAVE THEORY AND TECHNIQUES

AMIETE - ET

Time: 3 Hours

DECEMBER 2012

Max. Marks: 100

PLEASE WRITE YOUR ROLL NO. AT THE SPACE PROVIDED ON EACH PAGE IMMEDIATELY AFTER RECEIVING THE QUESTION PAPER.

NOTE: There are 9 Questions in all.

- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1 Choose the correct or the best alternative in the following: (2×10)

- a. A lossless transmission line of $Z_0=100\Omega$ is terminated by an unknown impedance. The termination is found to be at a maximum of the voltage standing wave and the VSWR is 5. What is the value of terminating impedance

(A) 500Ω
(C) 20Ω

(B) 100Ω
(D) 300Ω

- b. The value of series inductance (L) in Henries per Km for minimum attenuation in the loading of the transmission line is given by

(A) $L=CR/G$

(B) $L=G/CR$

(C) $L = \sqrt{CR/G}$

(D) $L = \frac{1}{\sqrt{GCR}}$

- c. The highest data speed is given by

(A) Coaxial cable link

(B) Microwave LOS link

(C) Microwave satellite system

(D) Optical fiber system

- d. For a two open-wire transmission line executed by a harmonically oscillating source with $\exp(-j\omega t)$ as the time factor, the voltage on the transmission line satisfy which one of the following relations

(A) $\frac{dv(x)}{dx} = -j\omega LI(x)$

(B) $\frac{dv(x)}{dx} = j\omega LI(x)$

(C) $\frac{dv(x)}{dx} = j\omega CI(x)$

(D) $\frac{dv(x)}{dx} = -j\omega CI(x)$

Code: AE72**Subject: MICROWAVE THEORY AND TECHNIQUES**

- e. Microwave link repeaters are typically 50 Km apart in TV transmission because of
- (A) Atmospheric attenuation
(B) Output power tube limitations
(C) Microwave transmission, which is through surface wave
(D) Earth's curvature
- f. A microwave junction is supposed to be matched at all ports if in the S matrix all diagonal elements are
- (A) zero (B) equal but not zero
(C) complex (D) equal but not complex
- g. A cavity is a
- (A) Low pass filter (B) High pass filter
(C) Band pass filter (D) Band stop filter
- h. In laboratory experiments, the output from reflex klystrons are modulated by square wave because
- (A) It is easy to generate square wave
(B) Crystal diode operates in the square law region
(C) It prevents frequency modulation
(D) Detector circuit is less complicated
- i. In a circular waveguide with radius r , the dominant mode is
- (A) TM_{01} (B) TE_{01}
(C) TM_{11} (D) TE_{11}
- j. Which one of the following is a transferred electron device?
- (A) BARITT diode (B) IMPATT diode
(C) Gunn diode (D) Step recovery diode

**Answer any FIVE Questions out of EIGHT Questions.
Each question carries 16 marks.**

- Q.2** a. Define the following terms and find their physical significance with reference to transmission lines. (8)
- (i) Characteristics impedance
(ii) Stub matching

Code: AE72**Subject: MICROWAVE THEORY AND TECHNIQUES**

- b. A typical transmission line has a resistance of $8\Omega/\text{Km}$, impedance of 2mH/Km and a capacitance of $0.002\mu\text{F/Km}$ and a conductance of $0.07\mu\text{s/Km}$. Calculate the characteristics impedance, attenuation constant, phase constant of the transmission line at a frequency of 2 KHz. If a signal of 2 Volt is applied and the line terminated by its characteristics impedance, calculate the power delivered to the load, if line length is 500 Km. (8)
- Q.3** a. Show that a TEM wave cannot propagate in a circular waveguide. (8)
- b. Determine the cut off wavelength for the dominant mode in a rectangular waveguide of breadth 10 cms. For a 2.5GHz signal propagated in this waveguide in the dominant mode; calculate the guide wavelength, the group and phase velocities. (8)
- Q.4** a. What are cavity resonators? Derive the expression for frequency for a rectangular and circulate cavity resonator. (8)
- b. Write short notes on: (8)
- (i) Rat Race Circuits (ii) Hybrid Tees
- Q.5** a. Explain Gunn effect diodes. (6)
- b. What are parametric devices? Describe advantages and disadvantages of parametric devices. (6)
- c. An up converter parametric amplifier has following parameters: (4)
- Ratio of output frequency over signal frequency, $f_o/f_s=25$, Figure of merit $\gamma Q=10$, Factor of merit figure, $\gamma=0.4$, Diode temperature, $T_d=350\text{K}$. Calculate:
- (i) Power gain in dB
- (ii) Noise figure in dB
- (iii) Band width
- Q.6** a. What are limitations of conventional tubes at microwave frequencies? How these limitations can be overcome? (8)
- b. Differentiate between Klystron from and TWT. (4)
- c. A reflex Klystron operates at 8GHz at the peak of $n=2$ mode with $V_o=300\text{V}$, $R_{sh}=20\text{K}\Omega$ and $L=1\text{mH}$. If the gap transit time and beam loading are neglected, find: (4)
- (i) repeller voltage
- (ii) beam current necessary to obtain an RF gap voltage of 200 V
- Q.7** a. What is linear magnetron? Explain its operation (6)
- b. Derive Hartree anode voltage equation for π mode. (6)

Code: AE72**Subject: MICROWAVE THEORY AND TECHNIQUES**

- c. A linear magnetron has the following parameters Anode voltage, $V_o=15kV$, Cathode current, $I_o=1.2A$, operating frequency, $f=8GHz$, Magnetic flux density, $B_o=0.015 \text{ wb/m}^2$, Hub thickness, $h=2.77 \text{ cm}$, Distance between anode and cathode, $d=5cm$. Calculate (4)
- (i) electron velocity at hub surface
 - (ii) phase velocity for synchronism
 - (iii) Hartree anode voltage
- Q.8** a. Explain microstrip lines and derive an expression for characteristic impedance for a microstrip line. (8)
- b. Explain ohmic losses in microstrip lines. (8)
- Q.9** a. Discuss the discrete, integrated and monolithic microwave. (8)
- b. Write short notes on: (8)
- (i) Thin film formation
 - (ii) Materials used for MMIC