


Electronics

Data Sheet

Resistors Preferred values for resistors (E24) series:
1.0, 1.1, 1.2, 1.3, 1.5, 1.6, 1.8, 2.0, 2.2, 2.4, 2.7, 3.0, 3.3, 3.6, 3.9, 4.3,
4.7, 5.1, 5.6, 6.2, 6.8, 7.5, 8.2, 9.1 ohms etc.

Resistor Printed Code (BS 1852) This code consists of letters and numbers:
R means $\times 1$
K means $\times 1000$ (i.e. 10^3)
M means $\times 1\,000\,000$ (i.e. 10^6)
Position of the letter gives the decimal point
Tolerances are given by the letter at the end of the code,
F = $\pm 1\%$, G = $\pm 2\%$, J = $\pm 5\%$, K = $\pm 10\%$, M = $\pm 20\%$.

| Resistor Colour Code | Number | Colour |
|----------------------|--------|--------|
| | 0 | Black |
| | 1 | Brown |
| | 2 | Red |
| | 3 | Orange |
| | 4 | Yellow |
| | 5 | Green |
| | 6 | Blue |
| | 7 | Violet |
| | 8 | Grey |
| | 9 | White |



Tolerance, gold = $\pm 5\%$, silver = $\pm 10\%$, no band = $\pm 20\%$

Silicon diode $V_F = 0.7\text{ V}$

Silicon transistor $V_{be} \approx 0.7\text{ V}$ in the on state, $V_{ce} \approx 0.2\text{ V}$ when saturated

Resistance $R_T = R_1 + R_2 + R_3 + \dots$ series

$$\frac{1}{R_T} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3} + \dots$$
 parallel

Capacitance $\frac{1}{C_T} = \frac{1}{C_1} + \frac{1}{C_2} + \frac{1}{C_3} + \dots$ series

$$C_T = C_1 + C_2 + C_3 + \dots$$
 parallel

Time constant $T = CR$, $T_{1/2} = 0.69 CR$

ac theory $I_{\text{rms}} = \frac{I_0}{\sqrt{2}}$

$$V_{\text{rms}} = \frac{V_0}{\sqrt{2}}$$

$$X_C = \frac{1}{2\pi fC}$$
 reactance

$$X_L = 2\pi fL$$
 reactance

$$f = \frac{1}{T}$$
 frequency, period

$$f_0 = \frac{1}{2\pi\sqrt{LC}}$$
 resonant frequency

This insert page should not be sent to the examiner

| Operational amplifier | $G_V = \frac{V_{out}}{V_{in}}$ | voltage gain | | | |
|--|---|------------------------------|------------------------------------|-------|--------------|
| | $G_V = -\frac{R_f}{R_1}$ | inverting | | | |
| | $G_V = 1 + \frac{R_f}{R_1}$ | non-inverting | | | |
| | $V_{out} = -R_f \left(\frac{V_1}{R_1} + \frac{V_2}{R_2} + \frac{V_3}{R_3} \right)$ | summing | | | |
| | $V_{out} = (V_+ - V_-) \frac{R_f}{R_1}$ | difference | | | |
| 555 Astable and Monostable | $T = 1.1RC$ | monostable | | | |
| | $t_H = 0.7 (R_A + R_B)C$ | astable | | | |
| | $t_L = 0.7 R_B C$ | | | | |
| | $f = \frac{1.44}{(R_A + 2R_B)C}$ | astable frequency | | | |
| Electromagnetic waves | $c = 3 \times 10^8 \text{ m s}^{-1}$ | speed in vacuo | | | |
| Assembler language microcontroller instructions | | | | | |
| Mnemonic | Operands | Description | Operation | Flags | Clock cycles |
| NOP | none | No operation | none | none | 1 |
| CALL | K | Call subroutine | stack \leq PC + 1 PC \leq K | none | 2 |
| RET | none | Return from subroutine | PC \leq stack | none | 2 |
| INC | R | Increments the contents of R | (R) \leq (R) + 1 | Z | 1 |
| DEC | R | Decrements the contents of R | (R) \leq (R) - 1 | Z | 1 |
| ADDW | K | Add K to W | W \leq W + K | Z, C | 1 |
| ANDW | K | AND K with W | W \leq W • K | Z, C | 1 |
| SUBW | K | Subtract K from W | W \leq W - K | Z, C | 1 |
| ORW | K | OR K and W | W \leq W + K | Z, C | 1 |
| XORW | K | XOR K and W | W \leq W \oplus K | Z, C | 1 |
| JMP | K | Jump to K (GOTO) | PC \leq K | none | 2 |
| JPZ | K | Jump to K on zero | PC \leq K if Z=1 | Z=1 | 2 |
| JPC | K | Jump to K on carry | PC \leq K if C=1 | C=1 | 2 |
| MOVWR | R | Move W to the contents of R | (R) \leq W | Z | 1 |
| MOVW | K | Move K to W | W \leq K | Z | 1 |
| MOVRW | R | Move the contents of R to W | W \leq (R) | Z | 1 |