MARK SCHEME for the October/November 2010 question paper

for the guidance of teachers

9691 COMPUTING

9691/11

Paper 1 (Written Paper), maximum raw mark 90

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes must be read in conjunction with the question papers and the report on the examination.

• CIE will not enter into discussions or correspondence in connection with these mark schemes.

CIE is publishing the mark schemes for the October/November 2010 question papers for most IGCSE, GCE Advanced Level and Advanced Subsidiary Level syllabuses and some Ordinary Level syllabuses.



	Page 2	Mark Scheme: Teachers' version	n Syllabus	Paper
	~	GCE A/AS LEVEL – October/Novembe	,	11
1	hardwa -Memor -provide -To con -Provide exampl -second -HCI/ex -Autom -allow c	trol the hardware of the computer/to ensure that e drivers/IO control y management/to ensure efficient use of memory a platform on which to run/load software/provide trol access to the computer/user IDs and passwore e utility programs/to aid with housekeeping, mate example of utility/description ample/description e.g. WIMP interface atic backup/description of a backup routine/increm pomputer to be used in different ways/description of thandling/example of a type of interrupt with actin nagement + example	translators for software. rds/security and privacy of aintenance/example utility, nental backup of a type of OS e.g. networ	system. /description of
	(Max 2	per -, max 4-, max 8)		[8]
2	(a) (i)	-The code produced by the programmer -in high-level language.		[2]
 (ii) -Source code is in human understandable language/the compution commands. The translator produces binary/machine code/executable form understand. (Accept machine readable if clear that candidate is referring to code.) 			executable form which the	computer can
	(b) (i) (ii)	-Error in the grammar (language rules) of the pro- Instruction to perform inappropriate arithmetic () [2]
	(c) (i) (ii)	 The testing of logical paths through the code All logical paths tests structure and logic of program use of a dry run (1 per -, max 2) Testing by members of software house Version may not be finished Testers have knowledge of programming/software 	are.	[2]
3	(a) (i)	 (1 per -, max 2) -Text/alpha/string/alphanumeric (not character) -These are sets of characters, not numbers/no c (second mark depends on the first) 	alculation involved with the	[2] em [2]
	(ii)	-Integer/byte -Must be whole number		[2]
	(iii)	-Boolean (accept yes/no, true/false, 0/1) -Only two possible values (yes/no)		[2]

	Ра	ge 3	Mark Scheme: Teachers' version	Syllabus	Paper
			GCE A/AS LEVEL – October/November 2010	9691	11
	(b)	-Records -Fields (i	I the data on all the students) comprise s (all the data about a single student) comprise ndividual pieces of data e.g. home telephone number) oints made on a diagram (only award one mark for the		[3]
4	(a)	-which ha -can be i	rt of the system which holds data as been collected from experts and nterrogated to find information points made in terms of this example e.g. info collected max 2)	from doctor	[2]
	(b)	-which th -These r Accept	ses <u>all</u> the rules that the system knows he expert system has to adhere to ules are applied to the knowledge to provide results (by points made in terms of this example e.g. sympt ge base to get diagnosis (= 2 marks) max 2)		
5	-Ea -Ba -Iter -Nu -Co -If < -no	ch item is rcode rea m code fo mber in s mparison reorder l	a control software bar coded d (on exit from shop/entrance to shop) ound on item file hop decremented/incremented made with reorder level evel then order placed if ng order yet made 6)		[6]
6	(a)	Software Network	C or Wireless network card/Server/wireless access po	int	[3]
	(b)		nts: rver/Switch at centre ral shown/Central storage		[3]
	(c)	-Number -either of -After da	rte has extra parity bit of ones in byte (+ parity bit) is set to… dd or even (dependent on parity) <i>(reject: byte is odd/ev</i> ta transmitted the parity is again calculated of the agreed odd or even then an error has occurred. max 4)	ven)	[4]

© UCLES 2010

www.XtremePapers.net

	Page 4	Mark Scheme: Teachers' version	Syllabus		Paper	
		GCE A/AS LEVEL – October/November 2010	9691		11	
7	e.g.					
	T = M = New	T = MFour = 0			(1)	
	READ M LET T =	1900 TO 2009 lean T + Mean			(1) (1) (1)	
	NEXT					
	LET M = $T/1^{2}$	10			(1)	
		ChosenYear senYear >= 1900) AND (ChosenYear <= 2006)			(1) (1)	
	FOR Year =	ChosenYear TO ChosenYear + 3			(1)	
	READ M LET Nev NEXT	lean vT = NewT + Mean			(1) (1)	
	LET MFour =	NewT/4			(1)	
		1 + 4 UTPUT "HOT" UTPUT "NORMAL"		} }	(1)	
	-Loop to read -with correct -Mean read in -Running tota -Calculation of -Input of year -loop to read -with correct -Mean read a -Mean of 4 year -Comparison -Two outcom	riable names used d all means condition nside loop al kept of mean of summer means outside loop r four means condition and cumulative total kept ears calculated outside loop with mean+4 les with sensible conditions				
	-validation of (1 per -, max	one of the inputs 10)			[′	10

	Page 5		Mark Scheme: Teachers' version	Syllabus	Paper
			GCE A/AS LEVEL – October/November 2010	9691	11
8	(i)	Dis: People do not act naturally if they are being watched/only see a snapshot.[2(ii) Adv. Detail can be explored/direction of enquiries can be altered			
	(ii)				[2]
	(iii) Adv. Shows how data is collected/shows data that needs to be collected/show information that needs to be output. Dis. Documentation often difficult for an outsider to understand/Privacy issue Relevance of files				
9	-pr	obabl	ue of measuring by callipers… y by shining laser light at metal and measuring shadow sensible method)	vs produced.	[2]
	(b) (i)		nge check <i>(or a description of range check)</i> ween a maximum which will fit in machine/minimum th.	must be greate	r than finished [2]
	(ii)	-Cor -Visi	ue input twice nputer compares two values, if different, then error ual check erator looks at value typed in as it appears on screen a	nd checks it is c	correct. [4]
10	-Printeo -On scr -Lights	d repo een ir or sou	to show temperatures of machines rts/hard copy/e.g. to show details of the day's output nage/e.g. showing progress of jobs on each machine und/e.g. to show alarm for machine, or a machine requ 3 -, max 6)	iring attention.	[6]
11	-Pr -e.	g. to a rinter g. to r	Illow operator to see immediate confirmation of inputs of the termination of inputs of the termination of termination o	(when changing	parameters)
	e.g		gnify that change is accepted/not passed validation pro max 2 pairs, max 4)	ocedures	[4]
	-Ar -In:	eas o structi	es a hard copy form f screen reserved for specific inputs ons can be supplied uttons/drop down lists		
	-In -Da	put ca ata to	ot allow any necessary data to be missed in be self-validating be input will be standard dependent on machine. max 3 of first four points, max 4)		[4]

Page 6	Mark Scheme: Teachers' version	Syllabus	Paper	
	GCE A/AS LEVEL – October/November 2010	9691	11	

12 -Worry about being made redundant

-Worry that they will not be able to cope with new system

-They will have to learn new skills

-new skills will mean better qualifications/more pay

-Much of tedium of job taken over by new system

-work may be made safer

-Management will be able to check up on their work through new system.

-de-skilling

(1 per -, max 5)

[5]