

Join discussion of this test paper at http://forum.gatementor.c

www.gatel

### **SECTION - A**

- StudentBounty.com 1. This question consists of TWENTY-FIVE multiple questions of ONE mark each. each question, four possible alternatives (A, B, C and D) are given, out of which ONLY ONE is correct. Indicate the correct answer in the boxes corresponding to the questions only on the FIRST sheet of the answer book.
- 1.1 Suppose that the expectation of a random variable X is 5. Which of the following statements is true?
  - (a) There is a sample point at which X has the value 5.
  - (b) There is a sample point at which X has value greater than 5.
  - (c) There is a sample point at which X has a value greater than or equal to 5.
  - (d) None of the above
- 1.2 The number of binary relations on a set with n elements is:
  - (a)  $n^2$ (b) 2<sup>n</sup>
  - (c)  $2^{n^2}$ (d) None of the above
- The number of binary strings of n zeroes and k ones that no two ones are 1.3 adjacent is Forum
  - (a)  $^{n-1}C_{k}$ (b)  ${}^{n}C_{k}$ (c)  ${}^{n}C_{k+1}$ (d) None of the above
- Consider the regular expression (0 + 1) (0 + 1)... N times. The minimum state 1.4 finite automation that recognizes the language represented by this regular expression contains
  - (a) n states (b) n + 1 states
  - (d) None of the above (c) n + 2 states
- 1.5 Context-free languages are closed under:
  - (a) Union, intersection (b) Union, Kleene closure
  - (c) Intersection, complement (d) Complement, Kleene closure
- Let  $L_D$  be the set of all languages accepted by a PDA by final state and  $L_E$  the set 1.6 of all languages accepted by empty stack. Which of the following is true?
  - (a)  $L_D = L_E$ (b)  $L_D \supset L_F$
  - (c)  $L_F = L_D$ (d) None of the above
- 1.7 Which of the following expressions is not equivalent to  $\bar{x}$ ?
  - (a) x NAND X (b) x NOR x (c) x NAND 1 (d) x NOR 1

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.co

www.gatel "um.gatementor.co "below? Which of the following functions implements the Karnaugh map shown below? 1.8

CD AB	00	00	11	10
00	0	0	1	0
01	х	Х	1	Х
11	0	1	1	0
10	0	1	1	0

- (a)  $\overline{A}B + CD$ (b) D(C + A) $(d)(C+D)(\overline{C}+D)+(A+B)$ (c) AD +  $\overline{AB}$
- Listed below are some operating system abstractions (in the left column) and the 1.9 hardware components (in the right column)?

	(A) Thread $ATEFO$	1. Interrupt
	(B) Virtual address space	2. Memory
	(C) File system	3. CPU
	(D) Signal	4. Disk
(a) (A) – 2 (c) (A) – 3	(B) - 4 (C) - 3 (D) - 1 (B) - 2 (C) - 4 (D) - 1	(b) (A) - 1 (B) - 2 (C) - 3 (D) - 4 (d) (A) - 4 (B) - 1 (C) - 2 (D) - 3

- Which of the following disk scheduling strategies is likely to give the best through 1.10 put?
  - (a) Farthest cylinder next (b) Nearest cylinder next
  - (c) First come first served (d) Elevator algorithm
- 1.11 System calls are usually invoked by using
  - (a) a software interrupt (b) polling
  - (c) an indirect jump (d) a privileged instruction
- 1.12 A sorting technique is called stable if
  - (a) it takes O (nlog n) time
  - (b) it maintains the relative order of occurrence of non-distinct elements
  - (c) it uses divide and conquer paradigm
  - (d) it takes O(n) space

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.c

- StudentBounty.com Suppose we want to arrange the n numbers stored in any array such that 1.13 negative values occur before all positive ones. Minimum number of exchanges required in the worst case is
  - (a) n 1 (b) n
  - (c) n + 1
    - (d) None of the above

www.gatel

1.14 If one uses straight two-way merge sort algorithm to sort the following elements in ascending order:

20, 47, 15, 8, 9, 4, 40, 30, 12, 17

then the order of these elements after second pass of the algorithm is:

- (a) 8, 9, 15, 20, 47, 4, 12, 17, 30, 40
- (b) 8, 15, 20, 47, 4, 9, 30, 40, 12, 17
- (c) 15, 20, 47, 4, 8, 9, 12, 30, 40, 17
- (d) 4, 8, 9, 15, 20, 47, 12, 17, 30, 40
- 1.15 The number of articulation points of the following graph is



- 1.16 If n is a power of 2, then the minimum number of multiplications needed to compute a\* is
  - (b) √*n* (a)  $\log_2 n$ (c) n -1 (d) n
- 1.17 Which of the following is the most powerful parsing method? (a) LL (1) (b) Canonical LR (c) SLR (d) LALR
- 1.18 Consider the join of a relation R with a relation S. If R has m tuples and S has n tuples then the maximum and minimum sizes of the join respectively are
  - (a) m + n and 0 (b) mn and 0
  - (c) m + n and |m n|(d) mn and m + n

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,

www.StudentBounty.com



Join discussion of this test paper at http://forum.gatementor.

StudentBounty.com 1.19. The relational algebra expression equivalent to the following tuple expression:

$$\left\{t \mid t \in r \land (t [A] = 10 \land t [B] = 20)\right\}$$
 is

- (a)  $\sigma_{(A=10\vee B=20)}(r)$
- (c)  $\sigma_{(A=10)}(r) \cap \sigma_{(B=20)}(r)$

(b) 
$$\sigma_{(A=10)}(r) \cup \sigma_{(B=20)}(r)$$
  
(d)  $\sigma_{(A=10)}(r) - \sigma_{(B=20)}(r)$ 

www.gate

1.20. Booth's coding in 8 bits for the decimal number -57 is

- (a) 0 100 + 1000(b) 0 - 100 + 100 -1
- (c) 0 1 + 100 10 + 1(d) 0 0 - 10 + 100 - 1
- 1.21. The maximum gate delay for any output to appear in an array multiplier for multiplying two n bit number is

(a)  $O(n^2)$ (b) O(n) (c) O(log n) (d) O(1)

- 1.22. The main memory of a computer has 2 cm blocks while the cache has 2 c blocks. If the cache uses the set associative mapping scheme with 2 blocks per set, then block k of the main memory maps to the set
  - (b) (k mod c) of the cache (a) (k mod m) of the cache

(c) (k mod 2c) of the cache (d) (k mod 2 cm) of the cache

- 1.23. The Newton-Raphson method is to be used to find the root of the equation f(x)=0where  $x_0$  is the initial approximation and f' is the derivative of f. The method converges
  - (b) only if f is a polynomial (a) always
  - (c) only if  $f(x_0) < 0$ (d) None of the above
- 1.24. Let R = (a, b, c, d, e, f) be a relation scheme with the following dependencies  $c \rightarrow f$ ,  $e \rightarrow a$ ,  $ec \rightarrow d$ .  $a \rightarrow b$ . Which of the following is a key for R? (b) EC (c) AE (a) CD (d) AC
- Which of the following is correct? 1.25
  - (a) B-trees are for storing data on disk and  $B^+$  trees are for main memory.
  - (b) Range queries are faster on B\* trees.
  - (c) B-trees are for primary indexes and B\* trees are for secondary indexes.
  - (d) The height of a  $B^*$  tree is independent of the number of records.

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.

www.gate

- StudentBounty.com 2. This question consists of TWENTY-FIVE sub-questions, of TWO marks each each of these sub-questions, four possible alternatives (A, B, C and D) are give out of which ONLY ONE is correct. Indicate the correct answers in the boxe corresponding to the questions only on the SECOND sheet of the answer book.
- Consider two events  $E_1$  and  $E_2$  such that probability of  $E_1$ ,  $Pr[E_1] = \frac{1}{2}$ , probability 2.1

of E<sub>2</sub>,  $\Pr[E_{21}] = \frac{1}{3}$ , and probability of E<sub>1</sub> and E<sub>2</sub>,  $\Pr[E_1 \text{ and } E_2] = \frac{1}{5}$ . Which of the following statements is/are true?

- (a)  $\Pr[E_1 \text{ or } E_2]$  is  $\frac{2}{3}$
- (b) Events  $E_1$  and  $E_2$  are independent
- (c) Events E<sub>1</sub> and E<sub>2</sub> are not independent
- (d)  $\Pr\left[\frac{E_1}{E_2}\right] = \frac{4}{5}$
- Two girls have picked 10 roses, 15 sunflowers and 15 daffodils. What is the 2.2. number of ways they can divide the flowers amongst themselves?
  - (b) 2100 CATE For(d) None of the above (a) 1638 (c) 2640
- Let L be a set with a relation R which is transitive, anti-symmetric and reflexive 2.3. and for any two elements a,  $b \in L$  let the least upper bound lub (a,b) and the greatest lower bound glb (a,b) exist. Which of the following is/are true?
  - (a) L is a poset

- (b) L is a Boolean algebra
- (c) -L1 is context free
- (d) -L2 is regular
- 2.4. If L is context free language and L2 is a regular language which of the following is/are false?
  - (a) L1 L2 is not context free (b)  $L1 \cap L2$  is context free (d) ~L2 is regular (c) ~L1 is context free
- 2.5. Given the programming constructs (i) assignment (ii) for loops where the loop parameter cannot be changed within the loop (iii) if-then-else (iv) forward go to (v) arbitrary go to (vi) non-recursive procedure call (vii) recursive procedure/function call (viii) repeat loop, which constructs will you not include in a programming language such that it should be possible to program the terminates (i.e., halting) function in the same programming language.
  - (a) (ii), (iii), (iv)
  - (b) (v), (vii), (viii)
  - (c) (vi), (vii), (viii)
  - (d) (iii), (vii), (viii)

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



2

3

### **GATE CS - 1999**

StudentBounty.com Join discussion of this test paper at http://forum.gatementor.c

www.gatel

- 2.6. For the schedule given below, which of the following is correct:
  - 1 Read
    - Read B
    - Write A
  - Read A 4
  - 5 Write A
  - 6 Write B
  - 7 Read B
  - Write B 8
  - (a) This schedule is serialized and can occur in a scheme using 2PL protocol
  - (b) This schedule is serializable but cannot occur in a scheme using 2PL protocol
  - (c) This schedule is not serialiable but can occur in a scheme using 2PL protocol
  - (d) This schedule is not seralisable and cannot occur in a scheme using 2PL protocol.
- 2.7. Consider the schema R = (S T U V) and the dependencies S  $\rightarrow$  T, T  $\rightarrow$  U. U  $\rightarrow$  V and V  $\rightarrow$  S. Let R = (R1 and R2) be a decomposition such that R1  $\cap$  R2 =  $\emptyset$ . The decomposition is
  - (a) not in 2NF

- Forun (b) in 2NF but not 3NF
- (c) in 3NF but not in 2NF

- (d) in both 2NF and 3NF
- 2.8. Consider the circuit shown below. In a certain steady state, the line Y is at '1'. What are the possible values of A, B and c in this state?



- (a) A = 0, B = 0, C = 1(b) A = 0, B = 1, C = 1
- (c) A = 1, B = 0, C = 1
- (d) A = 1, B = 1, C = 1
- 2.9. Which of the following sets of component(s) is/are sufficient to implement any arbitrary Boolean function?
  - (a) XOR gates, NOT gates
  - (b) 2 to 1 multiplexors
  - (c) AND gates, XOR gates
  - (d) Three-input gates that output (A.B) + C for the inputs A. B and C.



Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.

www.gatel

- StudentBounts.com 2.10. A multi-user, multi-processing operating system cannot be implemented hardware that does not support
  - (a) Address translation
  - (b) DMA for disk transfer
  - (c) At least two modes of CPU execution (privileged and non-privileged)
  - (d) Demand paging
- 2.11. Which of the following is/are advantage of virtual memory?
  - (a) Faster access to memory on an average.
  - (b) Processes can be given protected address spaces.
  - (c) Linker can assign addresses independent of where the program will be loaded in physical memory.
  - (d) Programs larger than the physical memory size can be run.
- 2.12. Which of the following actions is/are typically not performed by the operating system when switching context from process A to process B?
  - (a) Saving current register values and restoring saved register values for process В.
  - (b) Changing address translation tables
  - (c) Swapping out the memory image of process A to the disk.
  - (d) Invalidating the translation look-aside buffer.
- 2.13. Consider the following program in a language that has dynamic scooping:

var x: real;

procedure show:

begin print(x);end;

procedure small;

var x: real:

begin x: = 0.125; show; end;

begin x:=0.25;

show; small

```
end.
```

Then the output of the program is:

(a) 0.125 0.125 (b) 0.25 0.25 (c) 0.25 0.125 (d) 0.125 0.25

- 2.14. The number of tokens in the Fortran statement DO 10 I = 1.25 is
  - (a) 3 (b) 4
  - (c) 5 (d) None of the above

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,

Join discussion of this test paper at http://forum.gatementor

- 2.15. A grammar that is both left and right recursive for a non-terminal, is
  - (a) Ambiguous

(b) Unambiguous

www.gate

- StudentBounts.com (c) Information is not sufficient to decide whether it is ambiguous unambiguous
- (d) None of the above

2.16. The number of full and half-adders required to add 16-bit numbers is

- (a) 8 half-adders, 8 full-adders
- (c) 16 half-adders, 0 full-adders
- 2.17. Zero has two representations in
  - (a) Sign magnitude

(b) 1's complement

(b) 1 half-adder, 15 full-adders

(d) 4 half-adders, 12 full-adders

- (c) 2's complement (d) None of the above
- 2.18. Raid configurations of the disks are used to provide
  - (a) Fault-tolerance

- (b) High speed
- (c) high data density (d) None of the above
- 2.19. Arrange the following configuration for CPU in decreasing order of operating speeds: Hard wired control, -vertical microprogramming, horizontal microprogramming.
  - (a) Hard wired control, vertical micro-programming, horizontal microprogramming.
  - (b) Hard wired control, horizontal micro-programming, vertical microprogramming.
  - (c) horizontal micro-programming, vertical micro-programming, Hard wired control.
  - (d) vertical micro-programming, horizontal micro-programming, hard wired control.
- 2.20. The minimum number of record movements required to merge five files A (with 10 records), B (with 20 records), C (with 15 records), D (with 5 records) and E (with 25 records) is:
  - (a) 165 (b) 90 (c) 75 (d) 65
- 2.21. If  $T_1 = O(1)$ , give the correct matching for the following pairs:

$$\begin{array}{ll} (M) \ T_n = T_{n-1} + n & (U) \ T_n = O(n) \\ (N) \ T_n = T_n + n & (V) \ T_n = O(n \log n) \\ (O) \ T_n = T_n + n \log n & (W) \ T_n = O(n^2) \\ (P) \ T_n = T_{n-1} + \log n & (X) \ T_n = O(\log^2 n) \end{array}$$

#### www.StudentBounty.com nework Help & Pastpapers

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



- modes. Which of the following programming language features cannot be implemented on this processor?
  - (a) Pointers

(b) Arrays

- (c) Records
- (d) Recursive procedures with local variable
- 2.24. Consider the following C function definition
  - int Trial (int a, int b, int c)
  - {
- if ((a > = b) && (c < b) return b;

else if (a > = b) return Trial (a,c,b);

else return Trial (b,a,c);

}

The function Trial:

- (a) Finds the maximum of a, b, and c
- (b) Finds the minimum of a, b and c
- (c) Finds the middle number of a, b, c
- (d) None of the above
- 2.25. Which of the following is/are correct?
  - (a) An SQL query automatically eliminates duplicates
  - (b) An SQL query will not work if there are no indexes on the relations
  - (c) SOL permits attribute names to be repeated in the same relation
  - (d) None of the above

# SECTION - B

This section consists of TWENTY questions of FIVE marks each. Attempt ANY FIFTEEN questions. If more number of questions are attempted, score off the answer not to be evaluated, else only the first fifteen unscored answers will be considered.

3. (a) Mr. X claims the following:

> If a relation R is both symmetric and transitive, then R is reflexive. For this, Mr. X offers the following proof:

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.

www.gatel

"From xRy, using symmetry we get yRx. Now because R is transitive x yRx together imply xRx.

Therefore, R is reflexive".

- StudentBounty.com (b) Give an example of a relation R which is symmetric and transitive but not reflexive.
- Let G be a finite group and H be a subgroup of G. For  $a \in G$ , define  $aH = \{ah1\}$ 4. h∈H).
  - (a) Show that |aH| = |H|
  - (b) Show that for every pair of elements  $a, b \in G$ , either aH = bH or aH and bHare disjoint.
  - (c) Use the above to argue that the order of H must divide the order of G.
- 5. Let G be a connected, undirected graph. A cut in G is a set of edges whose removal results in G being broken into two or more components, which are not connected with each other. The size of a cut is called its cardinality. A min-cut of G is a cut in G of minimum cardinality. Consider the following graph.



- (a) Which of the following sets of edges is a cut?
- (i) {(A, B), (E, F), (B, D), (A, E), (A, D)]
- (ii) {(B, D), (C, F), (A,B)}
- (b) What is the cardinality of min-cut in this graph?
- (c) Prove that if a connected undirected graph G with *n* vertices has a min-cut of cardinality k, then G has at least (nk/2) edges.
- 6. (a) Given that A is regular and (A  $\cup$ B) is regular, does it follow that B is necessarily regular ? Justify your answer.
  - (b) Given two finite automata M1, M2, outline an algorithm to decide if  $L(M1) \subseteq$ L(M2). (note: strict subset)
- 7. Show that the language L{xcx 1 x  $\in$  {0,1}\* and c is a terminal symbol} is not context free c is not 0 or 1.
- 8. Let Abe an  $n \times n$  matrix such that the elements in each row and each column are arranged in ascending order. Draw a decision tree, which finds 1<sup>st</sup>, 2<sup>nd</sup> and 3<sup>rd</sup> smallest elements in minimum number of comparisons.

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.c

www.gate

StudentBounty.com 9. Let synthesized attribute val give the value of the binary number generated in the following grammar. For example, on input 101, 101, S.val = 5.625.

 $S \rightarrow LL \ L$ 

 $L \rightarrow LB \setminus B$ 

 $B \rightarrow 0 \setminus 1$ 

Write S-attributed values corresponding to each of the productions to find S.val.

10. Suppose we have a function HALTS which when applied to any arbitrary function f and its arguments will say TRUE if function f terminates for those arguments and FALSE otherwise. Example: Given the following function definition.

FACTORIAL (N) = IF (N = 0) THEN 1 ELSE N\*FACTORIAL (N-1)

Then HALTS (FACTORIAL 4) = TRUE and HALTS (FACTORIAL -5)=FALSE

Let us define the function. FUNNY (f) = IF HALTS (f f) THEN not (f f) ELSE TRUE

- (a) Show that FUNNY terminates for all functions f.
- (b) use (a) to prove (by contradiction) that it is not possible to have a function like HALTS which for arbitrary functions and inputs says whether it will terminate on that input or not.
- (a) Consider the following algorithms. Assume, procedure A and procedure B 11. take ( ) (1) and ( ) (1/n) unit of time respectively. Derive the time complexity of the algorithm in ()-notation.

```
algorithm what (n)
```

begin

```
if n = 1 then call A
else begin
```

what (n - 1);

call B(n)

end

end.

- (b) Write a constant time algorithm to insert a node with data D just before the node with address p of a singly linked list.
- 12. (a) In binary tree, a full node is defined to be a node with 2 children. Use induction on the height of the binary tree to prove that the number of full nodes plus one is equal to the number of leaves.
  - (b) Draw the min-heap that results from insertion of the following elements in order into an initially empty min-heap: 7, 6, 5, 4, 3, 2, 1. Show the result after the deletion of the root of this heap.

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,

> www.StudentBounty.com lomework Help & Pastpapers



Join discussion of this test paper at http://forum.gatementor.c

www.gatel

chudentBounts.com An instruction pipeline consists of 4 stages – Fetch (F), Decode field (D). Ex 13. (E) and Result Write (W). The 5 instructions in a certain instruction seque need these stages for the different number of clock cycles as shown by the table below.

No.	of	clock	cycles	needed	for
	01	CIOCIC	cy cico	necucu	101

Instruction	F	D	Ε	W
1	1	2	1	1
2	1	2	2	1
3	2	1	3	2
4	1	3	2	1
5	1	2	1	2

Find the number of clock cycles needed to perform the 5 instructions.

- 14. (a) Show that the formual  $[(\sim p \lor q) \Rightarrow (q \Rightarrow P)]$  is not a tautology.
  - (b) Let A be a tautology and B be any other formula. Prove that  $(A \lor B)$  is a tautology.
- What will be the output of following program assuming that parameter 15. passing is
  - (i) call by value
  - (ii) call by reference
  - (iii) call by copy restore

procedure P{x,y,z};

begin y: y + 1; z: x + x end;

begin

```
a: = : b : =3;
P(a+b,a,a);
Print (a)
```

end.

16. Consider the following Pascal program skeleton:

program sort (...);

```
var a,x,....;
procedure readarray;
     vari i, ....;
     begin
                          ...:=...a...
```

```
end;
```

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.co

www.gate Tom.gatementor.co procedure exchange (...); begin ...;=...a...; ....; =....*x*...; end; procedure qsort(....); var k,v, ....; function partition (...)...; var i,j,...; begin ...:=...a...; ...;=...v...; end; begin :

end:

begin

end.

Forum

Assume that given points in time during program execution, following procedures are active: sort, qsort (1,9), qsort (1,3), partition (1,3), exchange (1,3)

Show snapshots of the runtime stack with access links after each of the activations.

17. Consider the following program fragment in the assembly language of a certain hypothetical processor. The processor has three general purpose registers R1, R2 and R3. The meanings of the instructions are shown by comments (starting with ;) after the instructions.

X:	CMP R1,0	;	Compare R1 and 0, set flags appropriately in status register
	JZZ	;	Jump if zero to target Z.
	MOV R2, R1	;	Copy contents of R1 to R2
	SHR R1	;	Shift right R1 by 1 bit
	SHL R1	;	Shift left R1 by 1 bit
	CMP R2, R1	;	Compare R2 and R1 and set flag in status register
	JZY	;	Jump if zero to target Y
	INC R3	;	Increment R3 by 1;
Y:	SHR R1	;	Shift right R1 by 1 bit
	ЈМР Х	;	Jump to target X
Z:			

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,

#### www.StudentBounty.com lomework Help & Pastpapers



Join discussion of this test paper at http://forum.gatementor.

www.gate

- (a) Initially R1, R2 and R3 contain the values 5,0 and 0 respectively, who the final values of R1 and R3 when control reaches Z?
- StudentBounty.com (b) In general, if R1, R2 and R3 initially contain the values n, 0, and respectively. What is the final value of R3 when control reaches Z?
- Design a  $2K \times 8$  (2048 locations, each bit wide) memory system mapped at 18. addresses  $(1000)_{16}$  to  $(17FF)_{16}$  for the 8085 processor using four 1K  $\times$  4 memory chips. Each of these chips has the following signal pins:
  - (i) CS (Chip select, data lines are in high impedance state when it is 1)
  - (ii) RD (0 for read operation)
  - (iii) WR (0 for write operation)
  - (iv)  $A_0$ ,  $A_1$ , ...,  $A_9$  (input address lines.  $A_0$  is the lest significant)
  - (v) D<sub>0</sub>, D<sub>1</sub>, D<sub>2</sub>, D<sub>3</sub> (bi-directional data lines. D<sub>0</sub> is the least significant)
- 19. A certain computer system has the segmented paging architecture for virtual memory. The memory is byte addressable. Both virtual and physical address spaces contain 2<sup>16</sup> bytes each. The virtual address space is divi8ded into 8 nonoverlapping equal size segments. The memory management unit (MMU) has a hardware segment table, each entry of which contains the physical address of the page table for the segment. Page table are stored in the main memory and consists of 2 byte page table entries.
  - (a) What is the minimum page size in bytes so that the page table for a segment requires at most one page to store it? Assume that the page size can only be a power of 2
  - (b) Now suppose that the pages size is 512 bytes. It is proposed to provide a TLB (Translation look-aside buffer) for speeding up address translation. The proposed TLB will be capable of storing page table entries for 16 recently referenced virtual pages, in a fast cache that will use the direct mapping scheme. What is the number o tag bits that will need to be associated with each cache entry
  - (c) Assume that each page table entry contains (besides other information) 1 valid bit, 3 bits for page protection and 1 dirty bit. How many bits are available in page table entry for storing the aging information for the page? Assume that the page size is 512 bytes.
- 20. (a) A certain processor provides a 'test and set' instruction that is used as follows.

TSET register.flag

This instruction atomically copies flag to register and sets flag to 1. Give pseudopodia for implementing the entry and exit code to a critical region using this instruction.

(b) Consider the following solution to the producer-consumer problem suing a buffer of size 1. Assume that the initial value of account is 0. Also assume that the testing of count and assignment to count are atomic operations.

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,



Join discussion of this test paper at http://forum.gatementor.co

Producer

Repeat

StudentBounty.com Produce an item; *if* count = 1 *then* sleep; place item in buffer. Count =1: Wakeup (Consumer);

www.gatel

Forever

Consumer: Repeat

> if count = 0 *then* sleep; Remove item from buffer; Count = 0Wakeup (producer); Consumer item;

Forever:

Show that in this solution it is possible that both the processes are sleeping at the same time.



- Consider a B-tree with degree m. that is, the number of children, c, of any 21. internal node (except the root) is such that  $m \le c \le 2m -1$ . derive the maximum and minimum number of records in the leaf nodes for such a B-tree with height  $h.h \ge 1$ . (Assume that the root of a tree is at height 0).
- 22. Consider the set of relations

EMP (Employee-no. Dept-no, Employee-name, Salary)

DEPT (Dept-no. Dept-name, Location)

Write an SQL query to:

- (a) Find all employee names who work in departments located at 'Calcutta' and whose salary is greater than Rs.50,000.
- (b) Calculate, for each department number, the number of employees with a salary greater than Rs.1,00,000.

Join All India Mock GATE Classroom Test Series - 2007 conducted by GATE Forum in over 25 cities all over India. Question Papers including section tests and full tests are designed by IISc alumni according to the latest syllabus. Percentile, All India Rank, interaction with IISc alumni in our online discussion forums, and more. For more details,