

AMIETE – ET (NEW SCHEME)

Time: 3 Hours

DECEMBER 2011

Max. Marks: 100

NOTE: There are 9 Questions in all.

- Please write your Roll No. at the space provided on each page immediately after receiving the Question Paper.
- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 Minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1 Choose the correct or the best alternative in the following: (2×10)

- a. In a folded network with N subscribers, there can be maximum of _____ simultaneous calls.

(A) N/4 (B) N
(C) N/2 (D) 2N

- b. The letter B and S in BORSCHT stands for

(A) Batteryfeed & Supervisory Signalling
(B) Battery low & Security Alarming
(C) Bus Voltage & Signal Voltage
(D) Busy line Test & Supervision

- c. The larger the grade of service _____ is the service to customer

(A) Better (B) Worse
(C) No change (D) None

- d. Poission distribution formula for call arrived in a given time is

(A) $P(x) = \frac{A^x}{x!} e^{-A}$ (B) $P(x) = \frac{T^x}{x!} e^{-T}$
(C) $P(x) = \frac{\mu^x}{x!} e^{-\mu}$ (D) $P(x) = \frac{C^x}{x!} e^{-x}$

- e. The total number of crosspoint required for two stage connection is
- (A) $2N$ (B) $2\sqrt{2N}$
 (C) $2N^2$ (D) $2N^{3/2}$
- f. A fully connected three stage network requires large number of cross point when _____
- (A) Network is blocking (B) N is large
 (C) N is low (D) None of the above
- g. Availability of processor in SPC system is given by
- (A) $\frac{MTTF}{MTTR}$ (B) $\frac{MTTR}{MTTF}$
 (C) $\frac{MTTF}{MTTF + MTTR}$ (D) $\frac{MTTR}{MTTF + MTTR}$
- h. In outband signalling, frequencies from _____ KHz to _____ KHz are used for signalling.
- (A) 3.2, 3.8 (B) 3.8, 4.4
 (C) 3.7, 3.85 (D) 3, 3.6
- i. In circuit switched system all attempts to make call over a congested group of trunks are _____
- (A) Lost (B) Delayed
 (C) Successful (D) None
- j. In strowger exchange Final selector is used to select _____ digits of customer number
- (A) First two (B) Last two
 (C) Centre two (D) None

Answer any FIVE Questions out of EIGHT Questions.
Each question carries 16 marks.

- Q.2** a. With neat sketch explain functioning of a uniselector switch. (6)
- b. Design a 10,000 line exchange, show the connection between subscriber 9348 and 5569. (10)
- Q.3** a. Define
- (i) Erlang (ii) Holding time
- (iii) Grade of service (8)

- b. A group of 10 Trunks provide a grade of service of 0.01 when offered 10E Traffic.
- (i) How much is the grade of service improved if one extra trunk is added in the group?
 - (ii) How much does the grade of service deteriorate if one trunk is out of service?(8)
- Q4** a. What is grading? Write merits and demerits of grading. (8)
- b. Design a grading for connecting 20 trunks to switches having 10 outlets. (8)
- Q.5** a. Design Input controlled Time division space switch for 256 connection. (10)
- b. Explain the working principle of Time slot Interchange switch. (6)
- Q.6** a. Give signal exchange diagram for a local call and explain briefly. (8)
- b. Explain processor configuration used in SPC system. (8)
- Q.7** a. With neat sketch of out band signalling system, explain its working principle. (8)
- b. Draw block schematic of CCITT no.7 signalling system and explain briefly. (8)
- Q.8** a. Explain the principle of packet switching. Compare it with circuit switching. (8)
- b. List the features of ATM and explain the basic function of ATM switch. (8)
- Q.9** a. With neat sketch explain integrated digital network. (10)
- b. Explain the principle of cellular radio system. (6)