

AMIETE – ET (OLD SCHEME)

Code: AE14
Time: 3 Hours

Subject: ELECTROMAGNETICS AND RADIATION
Max. Marks: 100

JUNE 2011

NOTE: There are 9 Questions in all.

- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 Minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1 Choose the correct or the best alternative in the following: (2×10)

- a. By saying that the electrostatic field is conservative, we do not mean that
- (A) It is gradient of a scalar potential.
 - (B) The work done in a closed path inside the field is zero.
 - (C) Its curl is identically zero.
 - (D) The potential difference between any two points is zero.
- b. One of the following is not the a source of magnetic fields
- (A) A dc current in a wire.
 - (B) A permanent magnet.
 - (C) An accelerated charge.
 - (D) An electric field linearly changing with time.
- c. Maxwell's divergence equation for the magnetic field is given by
- (A) $\vec{\nabla} \times \vec{B} = 0$
 - (B) $\vec{\nabla} \cdot \vec{B} = 0$
 - (C) $\vec{\nabla} \times \vec{B} = \rho$
 - (D) $\vec{\nabla} \cdot \vec{B} = \rho$
- d. The electric and magnetic fields of an electromagnetic wave are related to one another by
- (A) They move in the same speed in the same direction.
 - (B) They are always perpendicular to one another.
 - (C) They are both perpendicular to the direction of propagation.
 - (D) All of the above.
- e. A 50 Ω lossless transmission line is terminated in 100 Ω load and excited by a 30 MHz source of internal resistance of 50 Ω . What should be the length of the transmission line for maximum power transfer
- (A) 5.0 m
 - (B) 1.25 m
 - (C) 2.5 m
 - (D) 10.0 m

- f. In which one of the following modes, transmission will be supported by rectangular wave guide?
- (A) TE_{10} (B) TE_{11}
 (C) TM_{11} (D) TM_{10}
- g. An antenna located in a city is a source of radio waves. How much time does it take the wave to reach a town 12,000 Km away from the city?
- (A) 36s (B) $20\mu s$
 (C) 20ms (D) 40ms
- h. In Sky wave propagation, sky distance is used
- (A) so as not to exceed the critical frequency.
 (B) to avoid the Faraday effect.
 (C) to prevent sky wave & upper ray interference.
 (D) to obey tilting.
- i. Magnetic flux density at a point distance R due to an infinitely long linear conductor carrying a current I^* is given by
- (A) $B = \frac{I}{2\mu\pi R}$ (B) $B = \frac{\mu I}{2R}$
 (C) $B = \frac{\mu I}{2\pi R}$ (D) $B = \frac{\mu I}{2\pi R^2}$
- j. Which of the following is scalar quantity?
- (A) Electric field strength (B) Electric potential
 (C) Electric displacement density (D) Force

Answer any FIVE Questions out of EIGHT Questions.
Each question carries 16 marks.

- Q.2** a. Define Electric field intensity at a point. Show & explain the variation of field with respect to distance. (4)
- b. Two point charges $Q_1=50\mu C$ at (-1, 1, -3) m and $Q_2=10\mu C$ at (3, 1, 0) Find the force on Q_1 due to Q_2 (6)
- c. Write & Explain Gauss's law with appropriate equation. Also give its modified version. (6)
- Q.3** a. Write both differential and integral form of Maxwell's equations in matter, as well as in free space. Mention clearly the notations used in the equations. (8)

- b. Write Boundary conditions for electric and magnetic field in mathematical form & also write the related statements. (8)
- Q.4** a. Write & explain: (8)
 (i) Faraday's law.
 (ii) Ampere's circuital law
- b. (i) Explain conduction current \bar{J} & its relation with \bar{E} (8)
 (ii) Explain concept of displacement current in magnetic field due to time varying electric field
- Q.5** a. Explain Poynting vector related to electrical power transmission. Derive the equation for Poynting's theorem. & give the physical significance of the related terms. (12)
- b. Define skin depth with respect to a good conductor. (4)
- Q.6** a. For transmission line with reactive & non-linear resistive element, derive the expression for voltage across the inductor & total current through the inductor. Also show these variations graphically. (11)
- b. What do you understand by SWR? Write the interpretation for $SWR = 1$ & $SWR = \infty$. (5)
- Q.7** a. What are the transmission modes that are possible at an operating frequency of 8GHz in a hollow rectangular wave guide of inner dimensions $4\text{cm} \times 5\text{cm}$. Find phase velocity, group velocity, cut-off wavelength & characteristic impedance for the dominant mode. (10)
- b. Define Polarization of waves and explain the three types of polarizations. (6)
- Q.8** a. Show that the radiation resistance of the Hertzian dipole for free space is given by (10)
- $$R_{rad} = 80\pi^2 \left(\frac{dl}{\lambda}\right)^2 \Omega$$
- b. A linear array of four isotropic antennas spaced apart $\lambda/2$ are fed in phase. Obtain the resultant pattern by using pattern multiplication technique. (6)
- Q.9** a. Define critical frequency for reflection of wave by the ionosphere. Show how it is dependent on the maximum ionization density for any given layer. (10)
- b. What are the possible propagation paths, when the energy radiated from the transmitting antenna may reach the receiving antenna? (6)