Code: AC10 Subject: DISCRETE STRUCT

AMIETE - CS (OLD SCHEME)

Time: 3 Hours

JUNE 2012

Max. Marks: 10

 (2×10)

PLEASE WRITE YOUR ROLL NO. AT THE SPACE PROVIDED ON EACH PAGE IMMEDIATELY AFTER RECEIVING THE QUESTION PAPER.

NOTE: There are 9 Questions in all.

- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1	Choose the correct or the best alternative in the following:	
-----	--	--

- a. If $A = \{x | 3 < x < 5\}$ and $B = \{y | 5 < y < 10\}$ then $A \cap B$ is equal to
 - (A) {5}

- **(B)** { }
- (C) $\{x \mid 3 < x < 10\}$
- **(D)** $\{3, 5, 10\}$
- b. Determinant of an Identity matrix of order 4 x 4 is _____.
 - **(A)** 16

(B) 0

(C) 4

- **(D)** 1
- c. A bag contains 15 pencils. These pencils are of four different colors. How many pencils must be of same colors?
 - **(A)** 4

(B) 5

(C) 3

- **(D)** 2
- d. A graph is called bi-connected if number of articulation point in it is equal to
 - **(A)** 3

(B) 2

 $(\mathbf{C}) 0$

- **(D)** 1
- e. Sum of rational and an irrational number is irrational can be proved using
 - (A) Direct proof.

- (B) Method of contradiction.
- **(C)** Mathematical Induction.
- (**D**) Method of contra positive.
- f. An asymmetric relation is not
 - (A) Symmetric

(B) Anti -symmetric

(C) Reflexive

(D) Symmetric & Reflexive

Student Bounts, com **Subject: DISCRETE STRUCT**

Which is not true about a bounded lattice?

- (A) It is always distributive
- (B) Zero and Unit element Exist
- (C) It has a least element
- (**D**) It has a greatest element

h. $p \rightarrow q \leftrightarrow \sim p \lor q$ is a

Code: AC10

(A) Contradiction

(B) Contingency

(C) Tautology

(**D**) Nothing can be said

Which of the following is not true about a tree?

- (A) A tree is a connected graph
- **(B)** A tree is acyclic
- (C) It is 1-seperable
- (**D**) There are multiple paths from root to a node.

A FSM recognizes a language of the following types

(**A**) Type 1

(B) Type 0

(C) Type 3

(D) Type 2

Answer any FIVE Questions out of EIGHT Questions. Each question carries 16 marks.

0.2 a. Find the sum of the following series

 $1*(1/2)+2*(1/2)^2+3*(1/2)^3+...$ **(8)**

- b. Given that f and g are two functions defined over set of real numbers R as f(x) = 1+x and g(x) = 1-x then find fof, fog, gof and gog.
- a. Using mathematical induction method, prove that $2^{2n+1}+3^{2n+1}$ is divisible by 5 Q.3 for any $n \in N$.
 - b. Read the following paragraph. Covert it into prepositional expression and show that the conclusion is true.

"Ram is a student and he is sincere. Every sincere student excels in the class." Shyam is also a sincere student. Therefore Ram and Shyam both excel in their class." **(8)**

a. Solve the following recurrence equation: **Q.4**

$$a_n + 3 a_{n-1} = n + 1 \text{ where } a_0 = 1$$
 (8)

b. A group of people contains 15 male and 7 female. Ramu, a male and Shyamala, a female are also in that group. A committee is to be formed of seven people containing 4 males and 3 females. What is probability that a committee formed of seven people will contain both Ramu and Shyamala? (8)

AC10 / JUNE - 2012

AMIETE - CS (OLD SCHEME)

2

Code: AC10 **Subject: DISCRETE STRUCT**

- Student Bounty Com **Q.5** Find the number of edges in the following graphs: Complete Graph (K_n), 5-Regular graph in n nodes, Complete bipartite graph $(K_{m,n})$ and N-Cube graph.
 - b. Write Warshall's algorithm for finding transitive closure of a relation.
- 0.6 a. Show that if a relation R defined on a set A is symmetric and transitive then R is not irreflexive. **(8)**
 - b. Given that $A = \{x \mid 0 < x \le 1\}$ then show that (A, \le) is an unbounded lattice. **(8)**
- **Q.7** a. Define prime implicant and minimize the following Boolean expression using Karnaugh Map

$$x' + xy + xyz + xy'z$$
 (8)

- b. Draw logic circuit diagram for Boolean function $F(x, y, z) = x \lor (x \land (y \lor z)) \land (x' \lor y)$ **(8)**
- **Q.8** a. Draw an expression tree for the infix expression $2 + \{3 - (4 + 5) / 3 * 4\} + 23$. Then traverse the tree in preorder and postorder and verify that the expressions so obtained are prefix and postfix notation respectively of the above expression.
 - b. Draw a finite state machine to recognize a regular expression a*(a+b)aab. Write its state transition table as well.
- **Q.9** Write short notes on **TWO** of the followings:
 - (i) Krushkal's algorithm
 - (ii) Equivalence Relation
 - (iii) Bounding elements in a poset

(8+8)