

## AMIETE – ET

Time: 3 Hours

JUNE 2013

Max. Marks: 100

PLEASE WRITE YOUR ROLL NO. AT THE SPACE PROVIDED ON EACH PAGE IMMEDIATELY AFTER RECEIVING THE QUESTION PAPER.

NOTE: There are 9 Questions in all.

- Question 1 is compulsory and carries 20 marks. Answer to Q.1 must be written in the space provided for it in the answer book supplied and nowhere else.
- The answer sheet for the Q.1 will be collected by the invigilator after 45 Minutes of the commencement of the examination.
- Out of the remaining EIGHT Questions answer any FIVE Questions. Each question carries 16 marks.
- Any required data not explicitly given, may be suitably assumed and stated.

Q.1 Choose the correct or the best alternative in the following: (2×10)

a. The total charge within some finite volume is

(A)  $\int_{\text{vol}} \rho_v dv$

(B)  $\int_{\text{vol}} \frac{\rho_v dv}{r}$

(C)  $\int_{\text{vol}} \frac{\rho_v}{r^2} dv$

(D)  $\int_s D \cdot ds$

b. The electric flux density at a point r from the point charge is

(A)  $\frac{q}{4\pi \epsilon r}$

(B)  $\frac{q}{4\pi r^2}$

(C)  $\frac{q}{4\pi r}$

(D)  $\frac{qr}{4\pi \epsilon}$

c. The potential difference between two points a and b is

(A)  $-\int_a^b E \cdot d\ell$

(B)  $-q \int_a^b E \cdot d\ell$

(C)  $\int_a^b E \cdot ds$

(D)  $q \int_a^b E \cdot ds$

d. The capacitance of an isolated spherical conductor of radius a is

(A)  $\frac{a}{4\pi \epsilon}$

(B)  $\frac{q}{4\pi \epsilon a}$

(C)  $\frac{4\pi \epsilon}{a}$

(D)  $4\pi \epsilon a$

Code: AE63 Subject: ELECTROMAGNETICS &amp; RADIATION

e. The poission's equation is

(A)  $\nabla^2 V = -\frac{\rho}{c}$

(B)  $\nabla^2 V = 0$

(C)  $\nabla^2 \bar{D} = \rho$

(D)  $\nabla \times \nabla \times \nabla = \rho$

f. The magnetic vector potential A and magnetic field B are related as

(A)  $A = \nabla \times B$

(B)  $B = \nabla \times A$

(C)  $B = \nabla \cdot A$

(D)  $A = \nabla \cdot B$

g. Lorentz force Equation is

(A)  $F = q(E + v \times B)$

(B)  $F = q(v \times B)$

(C)  $F = q(B + v \times E)$

(D)  $F = qE$

h. The characteristics impedance of free space is

(A)  $277\Omega$

(B)  $377\Omega$

(C)  $477\Omega$

(D) None of these

i. The maximum usable frequency is

(A)  $f_c \sec \theta$

(B)  $f_c \cos \theta$

(C)  $f_c \sin \theta$

(D)  $f_c \cot \theta$

j. The length of antenna operating at a frequency of 50MHz is

(A) 5.7m

(B) 57m

(C) 570m

(D) None of these

**Answer any FIVE Questions out of EIGHT Questions.  
Each question carries 16 marks.**

**Q.2** a. Find the expression for Electric field due to line charge. (8)

b. In the region of free space that includes the volume,  $2 < x, y, z < 3$ ,

$$D = \frac{2}{z^2} (yza_x + xza_y - 2xya_z) C/m^2.$$

(i) Evaluate the volume integral side of the divergence theorem for the volume defined here.

(ii) Evaluate the surface integral side for the corresponding closed surface. (8)

**Q.3** a. Derive an expression for calculating the capacitance of a parallel-plate capacitor. (8)

Code: AE63 Subject: ELECTROMAGNETICS &amp; RADIATION

- b. A non uniform electric field is given by  $E = y\mathbf{i} + x\mathbf{j} + z\mathbf{k}$ . Determine the work expended in carrying a charge of 2 coulomb from B(1,0,1) to A (0.8,0.6,1) along the shorter path of circle  $x^2 + y^2 = 1, z = 1$ . (8)
- Q.4** a. Show that the capacitance varies inversely as the square root of the voltage. (8)
- b. Using the Laplace equation, find the capacitance per unit length of a capacitor formed by two concentric circular cylinders of radius a and b ( $a < b$ ). (8)
- Q.5** a. The magnetic vector potential in spherical coordinates is given by  $A = 10r \sin\theta I_\theta$ . Find the flux density at  $\left(2, \frac{\pi}{2}, 0\right)$ . where  $I_\theta$  is unit vector in the direction of  $\theta$ . (8)
- b. Calculate curl H at origin, where  
 $H = 2y\mathbf{i} - (x^2 + z^2)\mathbf{j} + 3y\mathbf{k}$  (8)
- Q.6** a. Calculate the force between two linear, parallel, long conductors carrying currents in opposite direction. (8)
- b. Calculate self inductances and mutual inductances between two co-axial solenoids of radius 2 cm and 3cm carrying currents 2A and 3A having 50 and 80 turns/m respectively. (8)
- Q.7** a. Let  $\mu = 10^{-5}$  H/m,  $\epsilon = 4 \times 10^{-9}$  F/m,  $\sigma = 0$  and  $\rho_v = 0$ . Find k (including units) so that each of the following pairs of fields satisfies Maxwell's equations:  
 (i)  $\bar{D} = 6a_x - 2ya_y + 2za_z$  nC/m<sup>2</sup>,  $\bar{H} = kxa_x + 10ya_y - 25za_z$  A/m  
 (ii)  $\bar{E} = (20y - kt)a_x$  V/m,  $\bar{H} = (y + 2 \times 10^6 t)a_z$  A/m (8)
- b. Explain briefly about Retarded Potentials. (8)
- Q.8** a. Describe the following terms in connection with electro-magnetic waves: (8)  
 (i) Transverse waves (ii) Power density  
 (iii) Wave impedance (iv) Polarization
- b. Discuss the characteristics of antennas isolated from surfaces which will alter or change their radiation patterns and efficiency. (8)
- Q.9** a. Explain the radiation resistance of an antenna. (4)
- b. With sketch, describe the feed mechanism of a parabolic reflector (4)
- c. Write short notes on: (8)  
 (i) Horn Antenna  
 (ii) Helical Antenna